



Knowledge Base

powered by  **ALARM.COM**

Outdoor Wireless (ADC-V722W) - Data Sheet

1080p HD video recording and excellent low-light performance make the ADC-V722W Wi-Fi Video Camera from Alarm.com a powerful video solution for any location. With an IP66 rating, the ADC-V722W is weather-resistant, dust-tight, and ideal for capturing video indoors or outdoors.

Features

- HD 1080p video
- Waterproof and Dust-Tight
- IR night vision
- Wide dynamic range (WDR)

Included accessories

- Power Adapter (10 feet)
- Wi-Fi Video camera
- Quick Installation Guide
- Mounting hardware
- Video Analytics, Video Motion Detection, and sensor-triggered clips saved to the cloud





Specifications

Maximum resolution

1920x1080

Recording compression

H.264, MPEG-4

Image sensor

1/2.9" CMOS, 2.12 MP, 1920x1080

Lens

4.0 mm, F2.1



https://answers.alarm.com/ADC/Partner/Installation_and_Troubleshooting/Video_Devices/Outdoor_Wireless_ADC-V722W/O...

Updated: Thu, 21 Oct 2021 06:28:52 GMT

Angle of view	88°
Low-light sensitivity	0 lux with IR
IR range	Up to 12 meters (~40 feet)
Image adjustments	Flip, brightness, contrast, saturation, sharpness, exposure
Video motion detection	3 windows, adjustable sensitivity and threshold
Wireless connectivity	802.11 b/g/n/ac, 2.4 & 5 GHz
Ethernet connection	No
Simultaneous viewers	10
Operating temperature	-20°C – 50°C (-4°F – 122°F)
Operating humidity	20%-100% (non-condensing) RH
Max power consumption	12 V DC, 5 W
Dimensions (WxH)	2.4" x 4.4"
Ingress Protection	IP66
I/O Triggered Video Recording	For more information, see Outdoor Wireless - (ADC-V722W) Digital Input Trigger Guide .

Note: For information about frame rate (FPS), see [What is the frame rate for video?](#).



Network requirements

Minimum bandwidth

0.5 Mbps

For more information, see [What are the internet service and bandwidth requirements for Alarm.com video devices?](#).




LED guide



LED pattern	Status	Description
<p>Green Solid</p> 	Connected to internet	Local network and internet connection with Alarm.com IP.
<p>Green Flashing</p> 	Local network connection	Local network connection with local IP address, no internet. Note: If the LED does not go to a solid green after a few minutes, see Camera LED is blinking green .
<p>Red Solid</p> 	Power on, or no network connection	Power on, system booting up typically 60-90 seconds. If solid red for longer than 60-90 seconds, then there is no local or Internet connection.
<p>Red Flashing</p> 	Power on, or firmware update	Camera is powering on, or a firmware update is in progress.
<p>Blue Flashing</p> 	WPS mode	WPS mode is active. To enter WPS mode, press and hold the WPS button for about three seconds.
<p>White Flashing</p> 	AP mode	Wi-Fi access point (AP) mode is active. To enter AP mode, press and hold the WPS button for about six seconds.



<p>Red & Green Flashing</p> 	<p>Factory reset</p>	<p>The camera is restoring to factory default settings.</p> <p>Caution: If the camera is already installed, it may need to be removed from the Alarm.com account and re-added after a factory reset.</p> <p>To perform a factory reset, press and hold the WPS button for about 10-15 seconds.</p>
---	----------------------	---

Additional resources



Enroll in the [Video as a Service 201](#) training course today! For more information on accessing Academy Training, see [How can I access Academy Training?](#)

